

# Fundamental Dynamic Units: Feedforward Networks and Adjustable Gates

Herbert Sauro\* and Song Yang

Department of Bioengineering, University of Washington, Seattle, WA 98195, USA

Email: Herbert Sauro - hsauro@u.washington.edu; Song Yang - soyang@u.washington.edu;

\* Corresponding author

## Abstract

---

**Background:** The activation/repression of a given gene is typically regulated by multiple transcription factors (TFs) that bind at the gene regulatory region and recruit RNA polymerase (RNAP). The interactions between the promoter region and TFs and between different TFs specify the dynamic responses of the gene under different physiological conditions.

**Results:** By choosing specific regulatory interactions with up to three transcription factors, we designed several functional motifs, each of which is shown to perform a certain function and can be integrated into larger networks. We analyzed three kinds of networks: (i) Motifs derived from incoherent feedforward motifs, which behave as “amplitude filters”, or “concentration detectors”. These motifs respond maximally to input transcription factors with concentrations within a certain range. From these motifs homeostatic and pulse generating networks are derived. (ii) Tunable network motifs, which can behave as oscillators or switches for low and high concentrations of an input transcription factor, respectively. (iii) Transcription factor controlled adjustable gates, which switch between **AND/OR** gate characteristics, depending on the concentration of the input transcription factor.

**Conclusions:** This study has demonstrated the utility of feedforward networks and the flexibility of specific transcriptional binding kinetics in generating new novel behaviors. The flexibility of feedforward networks as dynamic units may explain the apparent frequency that such motifs are found in real biological networks.

---

## Background

In the last decade or so there have been significant advances in developing new high throughput technologies such as microarray, ChIP-Chip or ChIP-seq [2] to uncover large scale cellular networks. Understanding these networks has been facilitated by decomposing these networks into smaller parts, so-called motifs, with known structure and function [1]. Two major strategies currently exist for accomplishing this task. The first one, so called top-down analysis involves mining databases for recurring patterns of interacting genes [1,3,4], or in the case of signaling networks, proteins-protein interactions [5]. The emerging motifs are analyzed for function, especially the specific roles they might serve in a particular network. One interesting result from this work is the discovery of an enrichment in so-called feedforward motifs [6], Fig. 1 (a), a three gene network. Alon and colleagues [6–9] subsequently demonstrated the functionality of these motifs using both theory and experiment.

Another approach to understanding biological networks is the bottom-up approach [10]. Here knowledge of specific protein-DNA interactions and signaling proteins has allowed researchers to synthetically design gene regulatory networks. The design of these networks has resulted in the construction of a wide variety of network motifs such as oscillators, switches, and logic gates [?, 11, 12]. One of the goals of synthetic biology is to design simple networks that can behave as modules. In recent years there has been a resurgence of interest in the quantitative properties of gene regulatory networks [?, 13, 14]. In addition, the ability to carry out relatively precise measurements of gene activity using synthetic biology techniques [11] and single cell measurements [15, 16] has led to considerable progress in this field.

The top-down and bottom-up approaches are two ways to generate functional modules. Based on a few network motifs motivated by bottom-up approaches, we generated several novel functional network motifs by exploring additional transcriptional control mechanisms and combinations of feedforward networks.

One of the principles of gene regulation is regulated recruitment, where transcription factors bind to the promoter regions of a gene, recruiting other transcription factors and RNA Polymerase (RNAP) [17]. Furthermore, signaling molecules often activate some of these transcription factors through binding or phosphorylation. There are multiple ways by which these interactions take place, such as blocking the

promoter region, twisting the DNA, Histone modification, and DNA looping, *etc.* [18]. In addition, the combinatorial complexity of multiple transcription factors that bind to the same promoter region will also determine the transcription rate [19]. Given all this complexity, a very useful approach to model these kinds of interactions in gene regulatory networks is the Shea-Ackers approach [20]. In this work, we used this method to construct several different kinds of network motifs.

The network motifs we will discuss can be broadly classified into three categories. (1) Feedforward related motifs: obtained by additional feedbacks on the basic incoherent (type I) feedforward network [1]. (2) Tunable motif: This subnetwork can either behave as an oscillator or a bistable switch depending upon the concentration of a transcription factor. (3) Adjustable gates: This motif can switch between an AND and an OR gate depending upon the concentration of a transcription factor. All three network motifs arise from multiple transcription factor regulation at a particular gene. In designing these *in silico* networks, we didn't concern ourselves very much with exact mechanism such as DNA looping *etc.*, but rather focused on the architecture of the resulting network.

In the next section, we briefly review the Shea-Ackers approach, which is used to compute the transcription rate of genes. Then, we will describe three different kinds of models, amplitude filters, tunable motifs, and adjustable gates. The latter two behave functionally very differently depending upon the concentration of an input transcription factor. A discussion and summary can be found in the last section.

## Results and Discussion

### Modeling Gene Regulatory Networks Using Shea-Ackers Method

A common method for modeling protein-gene interactions is by using Michaelis-Menten or Hill function kinetics. However, in the models we will describe in this paper, all kinetics will be based on the Shea-Ackers formalism [20, 21]. This method estimates the probabilities for different transcription states from which an overall rate of transcription is derived. The approach is less empirical and more flexible than the standard methods and enables one to easily incorporate repressors and activators into the equation. In addition the formalism has a relatively straightforward relationship to the stochastic representations of gene expression models. Finally, the free energy terms in the formalism can be easily changed by altering the promoter region which enables the models based on Shea-Ackers to be tested experimentally.

We assume that the occupancy of the binding sites on promoters is governed by equilibrium statistical

thermodynamics probabilities [20–22]. The probabilities arise from the binding free energies, the free energies of interaction between transcription factors bound to adjacent sites, and the concentrations of the participating transcription factors and the RNA polymerase. This assumption holds when binding and unbinding to the promoter is rapid [21]. Slow binding has been shown to result in stochasticity due to operator occupancy fluctuations [23, 24], whereas for small concentrations, the individual birth and death of proteins introduce noise into the system [25].

We illustrate the Shea-Ackers method with a given gene regulated by two transcription factors,  $T_1$  and  $T_2$ . We assume that these three proteins bind at three distinct sites on the promoter, providing nine possible combinations of binding. Each combination is associated with a free energy that is proportional to the probability of this state and can be represented by the following equation [21]:

$$f = \exp(-\Delta G_f / k_B T) [T_1]^{n_1} [T_2]^{n_2} [R] \quad (1)$$

where  $\Delta G_f$  is the free energy difference of the bound and unbound states, and the factors  $[T_1]$  and  $[T_2]$  are the concentrations of transcription factors,  $R$  is the RNAP concentration and  $n_1$  and  $n_2$  are the number of monomers which combine into higher order multimers.  $k_B$  and  $T$  are the Boltzmann constant and absolute temperature respectively. From Eq (1) the normalized probability of a given state is then given by the ratio

$$Z_f = \frac{\exp(-\Delta G_f / k_B T) [T_1]^{n_1} [T_2]^{n_2} [R]}{\sum_1^9 \exp(-\delta G_f / k_B T) [T_1]^{n_1} [T_2]^{n_2} [R]} \quad (2)$$

If we assume that the rate of transcription is proportional to the relative probability when the polymerase is bound to the gene, then we can partition the states into the polymerase bound state ( $Z_{on}$ ) and the polymerase unbound state ( $Z_{off}$ ) [19]. The probability of gene expression is then:

$$P = \frac{Z_{on}}{(Z_{on} + Z_{off})}. \quad (3)$$

If a transcription factor is an activator, its free energy to bind with the RNAP will be very low, and hence this interaction will be favored. Whereas for an inhibitor, it would be highly improbable for RNAP to be recruited for transcription. Therefore, the interactions between the transcription factors and RNAP determine the regulatory rules, which we will explore in the next section for several different kinds of dynamical networks.

## Feedforward Related Motifs

First we assume that the dynamics lumps together transcription and translation into one process. Although explicit modeling and experiment has been shown to give rise to interesting effects such as protein bursts [25,26] or oscillations as a result of transcription delay [?], we believe that the main features of our models are captured by protein-DNA interactions.

### *Incoherent Type I Feedforward Related Networks*

High throughput approaches have uncovered several re-occurring motifs termed the feedforward motif [1,3]. Fig. 1(a) shows a common transcription factor for two genes, where the third gene is regulated in a feedforward fashion. Fig. 1(b) shows a protein-protein interaction in addition to this scheme. Feedforward motifs can lead to two types of dynamics depending on the nature of the two signals that converge on the third gene. Fig. 2 illustrates a functional representation of the schematic shown in Fig. 1(a) [6,7]. In this representation there are three different kinds of interactions: protein degradation, protein synthesis and gene regulation. In Fig. 2 the input transcription factor  $p_1$  modulates the activity of a target gene (G2) directly and indirectly through the gene product  $p_2$  of another gene (G1), which is also a transcription factor. The interaction between  $p_1$  and  $p_2$  at the promoter region of G2 and their ability to recruit RNAP determines the rate of transcription of Gene G2. This type of architecture has been shown [7–9] to lead to two types of dynamics depending on the nature of the regulation that occurs at the target gene G2. If  $p_1$ ,  $p_2$  are both activators, the gene circuit acts as a low pass filter, i.e. it is able to filter out transient signals and transcribe only when the input signal is long lived [6]. If  $p_1$ ,  $p_2$  regulate G2 as an activator and repressor respectively then the system can act as a bandpass filter, since the delayed response of  $p_1$  through  $p_2$  tends to suppress activity of G2 [7]. This has been suggested to be a general mechanism for speeding up response times in transcriptional networks [6,9]. Recently, it has also been argued that the steady state characteristics of such incoherent feedforward loops could be very important in establishing spatial stripes and pulsed temporal expression profiles of transcription factors involved in developmental processes [27].

### *Simple Feedforward*

We assume that  $p_1$  activates G1 and G2,  $p_2$ , the gene product of G1, is recruited by  $p_1$ , and the protein complex  $p_1p_2$  acts as a repressor of G2 (we assume that  $p_2$  cannot bind to G2 by itself). These

assumptions lead to the following rate equations,

$$\begin{aligned}\frac{d[p_2]}{dt} &= \frac{a_1 + a_2[p_1]}{1 + a_3 + a_4[p_1]} - \gamma_1[p_2] \\ \frac{d[p_3]}{dt} &= \frac{b_1 + b_2[p_1]}{1 + b_3 + b_4[p_1] + b_5[p_1][p_2]} - \gamma_2[p_3],\end{aligned}\tag{4}$$

where the transcriptional rates, and the “lumped” parameters are derived in the appendix.  $a_1, b_1$  represent leaky transcription, which is due to the probability that RNAP can bind to the operator region of the gene in the absence of a recruiting transcription factor. At steady state, before G1 is saturated with  $p_1$ ,  $p_2$  is proportional to  $p_1$ . The transcription rate for G2 (assuming negligible leaky transcription) can be approximated as,

$$T \propto \frac{b_1'[p_1]}{1 + b_2'[p_1] + b_3'[p_1]^2}\tag{5}$$

The transcriptional rate rises in proportion to  $p_1$  for small  $p_1$ , and falls in proportion to  $1/p_1$  for large values of  $p_1$ . Hence it reaches a maximum at some intermediate value of  $p_1$ .

In Fig. 3, we show the steady state values of  $p_2$  and  $p_3$  with respect to the input  $p_1$ . We note that the concentration of  $p_3$  has a maximum for a given value of  $p_1$ .

At low input concentration,  $p_1$  transcribes G2 and G1, and hence as its input level increases,  $p_2$  tends to grow. Recruitment of  $p_2$  by  $p_1$  at G2 makes it possible for the  $p_1p_2$  complex to halt further transcription of G2. This module is aptly named an “amplitude filter” (originally called a “band detector”, [12, 28, 29], since its output is maximal for a specific range of input. Such biphasic response has also been discussed in other systems [30, 31]. Recently, Ishihara et. al. [27] discussed the band properties of such networks and used this to explain pulsed behavior and patterning in *Drosophila* developmental processes.

### *The effect of dimerization*

In this section we will consider the effect of dimerization of  $p_2$ , before it binds to the regulatory region of G2. Dimerization has been shown to be important to reduce the effects of stochastic fluctuations [32] in a feedforward regulatory scheme. Here we discuss the steady state behavior of a network regulated by  $p_1$ , which recruits a dimer of  $p_2$ , and this complex is a repressor at G2. The only changes that need to be made to Eq. 4 are to include the dimerization equations. These modified equations are,

$$\begin{aligned}
\frac{d[p_2]}{dt} &= \frac{e_1 + e_2[p_1]}{1 + e_3 + e_4[p_1]} - \gamma_1[p_2] - 2(k_{d1}[p_2]^2 - k_{d2}[p_d]) \\
\frac{d[p_3]}{dt} &= \frac{d_1 + d_2p_1}{1 + d_3 + d_4p_1 + d_5p_1p_d} - \gamma_2p_3 \\
\frac{dp_d}{dt} &= k_{d1}[p_2]^2 - k_{d2}[p_d] - k_{d3}[p_d]
\end{aligned} \tag{6}$$

where in addition to the formation and dissociation of the dimer complex, the dimer can also degrade. With these equations it is easy to compute the steady state values of  $p_3$  with respect to the input  $p_1$ . In Fig. 4, we plot the steady state value of  $p_3$  as a function of  $p_1$  in the upper panel, which shows a much steeper fall off of the amplitude filter curve, compared to the simple feedforward case discussed earlier. The amplitude filter in this case, has a narrower bandwidth, and hence its filtering capabilities of the input transcription factor  $p_1$  are much more enhanced. The sharp fall off is due to the quadratic dependence of the amount of dimer with respect to the input; as the input  $p_1$  increases the amount of available dimer  $p_d$  to be recruited by  $p_1$  at G2 increases, thus increasing the amount of repression at G2. Dimerization of  $p_1$  has the effect of increasing both the width and shifting the peak of the amplitude filter curve.

#### *Effects of mutations at G1 and G2*

We now discuss the effects of two types of mutations at the binding sites at G1 and G2, for the simple feedforward with dimerization of  $p_2$ . Similar qualitative results can be obtained for the simple feedforward and mixed feedforward. In general, a mutation at the binding site tends to change the free energy of binding of the transcription factor, generally decreasing the binding affinity. In Fig. 4(a), a mutation at G1 reduces the ability of  $p_1$  to bind to it. Hence larger amounts of  $p_1$  are required to achieve the same transcription rate thereby shifting the amplitude filter peak to the right. In Fig. 4(b), a mutation at G2 reduces the ability of  $p_2$  to be recruited to G2. This leads to a slower fall off, since repression does not take place very efficiently. The two types of mutations can be used to engineer the shape of the amplitude filter, by changing its bandwidth and peak value [?].

### Mixed Feedforward Motifs

In Fig. 5, we show a slightly different feedforward scheme, which is a functional interpretation of Fig. 1b. The gene product  $p_2$  is shown as an activator of G2, whereas  $p_1$  is a repressor of G2. Also indicated in the figure is a protein-protein interaction, whereby the input  $p_1$  binds to  $p_2$ , and targets it for degradation.

We assume that  $p_1$  activates G1 leading to the production of  $p_2$ ;  $p_2$  can individually bind to G2 and act as an activator. Furthermore  $p_1$  can be recruited by  $p_2$  at the operator region of G2, and together this complex acts as a repressor.  $p_1$  binds to  $p_2$  and actively degrades it. One possible mechanism by which this can occur is if  $p_1$  labels  $p_2$  with ubiquitin molecules for proteolytic degradation [33]. The above assumptions lead to the following rate equations,

$$\begin{aligned}\frac{d[p_2]}{dt} &= \frac{c_1 + c_2[p_1]}{1 + c_3 + c_4[p_1]} - \gamma_c[p_1][p_2] - \gamma_1[p_2] \\ \frac{d[p_3]}{dt} &= \frac{d_1 + d_2[p_2]}{1 + d_3 + d_4[p_1] + d_5[p_2] + d_6[p_1][p_2]} - \gamma_2[p_3],\end{aligned}\tag{7}$$

where the transcriptional rates, and the “lumped” parameters are derived in the appendix. In the equation for  $p_2$ , the extra degradation term is due to the protein-protein interaction between  $p_1$  and  $p_2$ . For this system of equations the plots shown in Fig. 6 show the behavior of the steady state value of  $p_3$ , demonstrating the amplitude filter effect.

As  $p_1$  increases,  $p_2$  begins to grow and transcribe G2; however, two key factors prevent G2 from being continually transcribed with further increases in  $p_1$ . The first is that  $p_2$  is targeted by  $p_1$  for degradation, and the second is that  $p_2$  binds to G2 and recruits  $p_1$ , which turns off the transcription.

In both the simple incoherent Type I feedforward, with/without dimerization, as well as the mixed feedforward, we have shown how it is possible to obtain a basic amplitude filter. The property of such an amplitude filter can now be further exploited to generate new types of networks when additional feedbacks are added to this basic motif.

### Application 1: Time Ordering

The amplitude filter or “concentration detector” has been shown to perform temporal processing functions such as pulse generation [28]. Pulse-like behavior has been simulated in [27], with a series of cascaded feedforward loops, which in fact use the amplitude filter property of the networks to generate pulsatile behavior. We use a similar idea where a single transcription factor could serve as an input to several



amplitude filters, each of which has a different shape. In particular we assume that for each amplitude filter module, the peaks of  $p_3$  occur at different input transcription factor ( $p_{1opt}$ ) concentration values. Then, as the input concentration crosses  $p_{1opt}$ , the amplitude filters get activated in a sequence, depending on how far apart  $p_{1opt}$  are for different amplitude filters [7].

A single input can therefore activate several genes in a sequence. One example could be the sequential release of different proteins required in a certain developmental process.

Fig. 8a plots  $p_3$  as a function of the input transcription factor concentration, showing a shifted peak for the two amplitude filters with respect to the same input transcription factor. In Fig. 8b, the temporal profile for the outputs are shown assuming that the input concentration is ramped up as a function of time. This leads to an ordered protein production in time.

Kashtan et. al. [34], have explored the consequences of multi-output networks regulated by feedforward networks. They show through simulations that in some of these cases feedforward loops with a common input can regulate genes in a temporal order. Such temporal order can occur in multi-output feedforward loop systems such as in the *E. coli* flagellar synthesis regulation systems, where proteins need to be assembled in a timed fashion to make up the flagellar basal-body motor [35]. It has also been found in [36], that the logic of the program of gene transcription during differentiation in *Bacillus Subtilis* sporulation involves a series of feedforward loops that generate gene transcription in a pulse like manner.

## Application 2: Homeostatic Networks

Homeostatic networks are important in several biological systems. One example in which homeostasis has been shown to occur through integral feedback control is in the chemotaxis network in *E. coli* ([37]). Our motivation was to design a network using the amplitude filter which would display homeostasis to input perturbations.

Using the output of the amplitude filter module as an input to itself, one can construct the motif shown in Fig. 9(a), where the filter module's output  $p_3$  participates as a transcription factor for gene G1, whose protein product  $p_1$  serves as the input to the filter module. The feedback could be positive or negative, depending on whether the amplitude filter output  $p_3$  is an activator or repressor of G1. In addition, an external input protein A can bind as an activator to gene G1. Depending on the interaction between the

input control  $A$ , the feedback  $p_3$ , and RNAP, we obtain different types of behavior. Consider  $p_3$  as an activator of G1 in Fig. 9(a), we assume that the interaction between  $A$ ,  $p_3$  and RNAP is such that we obtain an **AND** gate at G1, *i.e.* G1 expresses only when both  $A$  and  $p_3$  are present. The equation that describes the additional variable,  $p_1$ , is given by

$$\frac{dp_1}{dt} = \frac{u_1 + u_2[A][p_3]}{1 + u_3 + u_4[A] + u_5[p_3] + u_6[A][p_3]} - \gamma_3 p_1 \quad (8)$$

which is the equation for the input of the amplitude filter, and the equation for  $p_3$ , the output of the amplitude filter, is the same as in Eq 6. The steady state plot for the output  $p_3$  as a function of the input  $A$ , is shown in Fig. 10(a).

Figure 10 shows that the steady state values of  $p_3$  are constant even for large inputs. As the input  $A$  of the filter module increases, the output  $p_3$  decreases (assuming that  $p_3$  is maximal at the initial value of  $A$ ).

This is because the input transcription factor concentration moves away from  $p_{1opt}$ , at which the maximal value of transcription occurs. Therefore, this decreases the transcription of the filter module, and since its output feeds back as an activator to G1, its input level tends to decrease the transcription of G1.

Essentially the filter module balances the increase in the input  $A$  to G1 by decreasing its output. As seen in the lower plot of Fig. 10(a),  $p_3$  stabilizes to an almost fixed value even though the input control  $A$  increases in time. This is an example of a homeostatic gene network which fixes its response to input transcription factor concentrations. The other case shown in the scheme in Fig. 10(b), where  $p_3$  is a repressor for G1. In the regulation at G1,  $A$  as an activator and  $p_3$  is a repressor. The negative feedback of  $p_3$  into G1 suppresses the input to the amplitude filter. If  $A$  decreases, the input to the filter module  $p_1$  also decreases, this reduces the transcription rate (assuming that at steady state the value of  $p_3$  is maximal). This then lifts the repression from G1, and the input to the filter module increases, thereby balancing the effect due to the reduced input  $A$ , and achieving the same steady state as before. The above two circuits produce a fixed amount of output proteins, even though the input might vary by a large amount. In the first case it is homeostatic to an increase in the concentration value of the input transcription factor, in the second case it is homeostatic with respect to a decrease in the input concentration.

## Tunable Motifs

In this section we discuss an example of a gene network that exhibits oscillatory dynamics at small values of an input transcription factor, and bistability for high input values. This network therefore implements

two different types of motif functionality, depending upon the concentration of an input transcription factor. Recently Voigt et. al. [38] discussed a model of a network in the *Bacillus* sporulation pathway, which was shown to exhibit one of two alternatives, i.e. either a bistable switch or oscillatory behavior, depending on the environmental conditions. A synthetically constructed network exhibiting multifunctionality in *E. coli* [39] was demonstrated to be able to flip function from an oscillator to a switch, by removing a particular interaction.

There are now several examples of synthetically designed genetic networks such as switches [40, 41] and oscillators [11, 42] that use the common rules of mutual inhibition and activation to achieve a desired functional behavior. The network we will describe is motivated by the work of Gardner et. al. [40], where the authors designed a toggle switch. In [43], it was discussed how a toggle switch could be converted into a relaxation oscillator by suitably manipulating the basic toggle switch network by adding extra regulation. We further extend this design by introducing a new type of regulation, which involves an external transcription factor whose concentration can flip the system function between an oscillator and a switch.

Fig. 11 shows two mutually repressing genes, G1 and G2. The repression is assumed to occur through tetramer binding of each of their gene products,  $p_1$  and  $p_2$ , the gene products of G1 and G2, ( $p_1$  binds to G2, and  $p_2$  binds to G1). Hence, if these were the only interacting genes in the network, the system could be in one of two stable states, i.e., G1 is fully expressed, and G2 is silent or *vice versa*. Gene G3 is activated by  $p_2$ , and its product  $p_3$  further activates G1. The feedback of  $p_3$  to G1 has the effect of turning the bistable switch into a relaxation oscillator [43]. Assuming that initially G2 is **ON**, which causes G3 to get transcribed and  $p_3$  to grow,  $p_3$  then activates gene G1, leading to the growth of  $p_1$ . Thus G1 switches to a high state, which ultimately shuts down gene G2 due to its repressive effects. This leads to a decrease in  $p_3$  which subsequently turns G1 **OFF**, thereby completing one cycle of relaxation oscillations.

Consider now an extra piece of regulation, an external input  $A$ , as an activator of gene G1.  $A$  can bind to the promoter region and activate G1, but can also cooperatively bind with the tetramer of  $p_2$ , which represses G1.  $p_3$  can also bind cooperatively with the tetramer of  $p_2$ , which has the effect of repressing G1. The two activators  $A$  and  $p_3$ , however, are assumed to be mutually exclusive, i.e. both  $A$ , and  $p_3$  cannot bind together, but each can individually bind to the DNA. As described in the Appendix, these regulatory rules make G1 behave like an **OR** gate with respect to the inputs  $A$  and  $p_3$ . From the above regulatory mechanisms, the following equations for the protein dynamics emerge,

$$\begin{aligned}
\frac{dp_1}{dt} &= \frac{m_1[A] + m_2[p_3]}{1 + m_3[A] + m_4[p_2]^4 + m_5[A][p_2]^4 + m_6[p_3] + m_7[A][p_3]} - \gamma_1 p_1 \\
\frac{dp_2}{dt} &= \frac{n_1}{1 + n_2 + n_3[p_1]^4} - \gamma_2 p_2, \\
\frac{dp_3}{dt} &= \frac{o_1 + o_2[p_2]}{1 + o_3 + o_4[p_2]} - \gamma_3 p_3,
\end{aligned} \tag{9}$$

We now consider approximating the transcription rate for G1 for small and large values of the control transcription factor,  $A$ . For small  $A$ ,

$$T \simeq \frac{m_2[p_3]}{1 + m_4[p_2]^4 + m_6[p_3] + m_7[p_2]^4[p_3]} \tag{10}$$

G1 is activated by  $p_3$ , and repressed by  $p_2$ . As discussed earlier  $p_3$  toggles the bistable switch formed between the gene products of G1 and G2. For large  $A$ ,

$$T \simeq \frac{1}{\frac{m_3}{m_1} + \frac{m_5}{m_1}[p_2]^4} \tag{11}$$

which is the transcription rate, one would obtain a toggle switch, between G1 and G2. When  $A$  is large, it is more likely for  $A$  to bind to the DNA than its competitor  $p_3$  and the system is put into the bistable regime. The input  $A$  can therefore be used to tune the system into a relaxation oscillator, or a switch. Fig. 12 shows the bifurcation plot for the steady state values of  $p_1$  as a function of the input transcription factor  $A$ . The plot shows a subcritical Hopf bifurcation [44, 45] for  $p_1 \simeq 9$ , and a saddle-node bifurcation at  $p_1 \simeq 35$ . As discussed earlier, the system exhibits oscillations for  $A < \simeq 11$  and bistability for  $A > \simeq 35$ . In the right panel of Fig. 12, the time series plots for  $p_1, p_2, p_3$ , are displayed, which show oscillations, for the case where  $A = 1$ . In the lower right panel of Fig. 12 the bistable behavior of  $p_1$  is displayed (for the input  $A = 50$ ), taking one of two values, depending on the initial conditions.

## Adjustable Gates

The transcriptional interaction between two transcription factors and RNAP has previously been shown to generate several instances of logic such as **AND**, **OR**, **XOR**, *etc.* [19]. Multiple transcription factors can regulate the gate properties of a network through their input concentrations. Alon and colleagues [46] have studied the gate properties of the regulation of the *lacZYA* operon in *E. coli*; and by using a mathematical model, their work shows that the regulation can be made to behave as a fuzzy AND, a pure AND, and an OR logic gate. In this section we consider gene regulation by three transcription factors which have the

property of switching between two different logical functions, depending on one of the input transcription factor concentrations. Further we propose that such a circuit with appropriate feedback can be made to exhibit other kinds of functionality such as homeostasis or oscillatory behavior.

Consider gene G1 transcribed by the interaction of three transcription factors,  $p_1$ ,  $p_2$  and  $p_3$ .  $p_3$  is the control that determines the output logic. We make the following assumptions: binding of all three transcription factors and RNAP to the gene is unlikely; individual binding of  $p_1, p_2, p_3$  and RNAP is also unfavorable; we also assume that transcription is not leaky. With these assumptions, transcription occurs due to the binding of the following complexes  $p_1p_2P, p_1p_3P, p_2p_3P$ . The transcription rate, takes the following form,

$$T = \frac{r_1p_1p_2 + r_2p_1p_3 + r_3p_2p_3}{1 + r_4p_1 + r_5p_2 + r_6p_3 + r_7p_1p_2 + r_8p_1p_3 + r_9p_2p_3 + r_{10}p_1p_2p_3} \quad (12)$$

The above formula can be simplified for two cases, i.e. high and low values of the concentration of the control transcription factor,  $p_3$ . For low values of  $p_3$ ,

$$T \simeq \frac{r_1p_1p_2}{1 + r_4p_1 + r_5p_2 + r_7p_1p_2} \quad (13)$$

which implies that the transcription is activated only when both  $p_1$  and  $p_2$  are present, implementing an **AND** gate. For high values of  $p_3$ , the transcription rate is,

$$T = \frac{r_2'p_1 + r_3'p_2}{1 + r_8'p_1 + r_9'p_2 + r_{10}'p_1p_2} \quad (14)$$

where  $r_i' = \frac{r_i}{r_6}$ , for  $i = 2, 3, 8, 9, 10$ . Here the transcription is activated when either  $p_1$  or  $p_2$  is present, implementing an **OR** gate. The control  $p_3$  is able to switch from an **AND** to **OR** gate. In Fig. 13 we plot the transcription rates as a function of the input transcription factors,  $p_1$  and  $p_2$ .

The ability to switch from one kind of logical function to another by varying the control  $p_3$  opens up the possibility to use such a motif in a gene network with other interacting genes. Consider Fig. 14(i), a regulatory circuit with G1 having three inputs  $p_1, p_2$  and the control  $p_3$ , which emerges from a long negative feedback loop from its gene product  $p_5$  in the following way: The gene G2 constitutively produces protein  $p_4$ , which forms a protein complex with  $p_5$ .  $p_4$  is also a transcription factor for the gene G3, which produces protein  $p_3$ , and hence this is how a feedback into G1 is achieved. We further assume that  $p_4$  binds to the regulatory region of G3 as a tetramer. The transcription factors  $p_1$  and  $p_2$  are assumed to be external to the system, and can be either set to a constant or a time dependent value. In our case we shall fix the value of  $p_2$ , but allow  $p_1$  to fall to low levels, starting at some fixed value. However, the dynamics of

the network is symmetric with respect to  $p_1$  and  $p_2$ , and hence we could have equally well chosen to vary  $p_2$  and keep  $p_1$  fixed. Fig. 15 shows the logical structure for the adjustable gate network. Note that the output from the gate determines its behavior. The differential equations for the rates of production of the various species are,

$$\begin{aligned}
\frac{d[p_5]}{dt} &= \frac{r_1[p_1][p_2] + r_2[p_1][p_3] + r_3[p_2][p_3]}{1 + r_4[p_1] + r_5[p_2] + r_6[p_3] + r_7[p_1][p_2] + r_8[p_1][p_3] + r_9[p_2][p_3] + r_{10}[p_1][p_2][p_3]} \\
&- k_1[p_4][p_5] + k_2[C] - \gamma_{p_5}[p_5], \\
\frac{d[C]}{dt} &= k_1[p_4][p_5] - k_2[C], \\
\frac{d[p_4]}{dt} &= c_0 - k_1[p_4][p_5] + k_2[C] - \gamma_{p_4}[p_4], \\
\frac{d[p_3]}{dt} &= \frac{v_2[p_4]^4}{1 + v_4[p_4]^4} - \gamma_{p_3}[p_3],
\end{aligned} \tag{15}$$

For gene G1, the input  $p_2$  is held constant, but the input  $p_1$  is made to decay from some initial value. Gene G2 produces  $p_4$  constitutively, and is sequestered by the output of G1, *i.e.*  $p_5$ , into the complex  $C$ . Since  $p_4$  is a transcription factor for G3, its sequestration away from G2 results in a lower value of the protein  $p_3$ . Hence the control  $p_3$  is changed, the gate properties of G1 switch between **AND/OR**. The negative feedback arising from G1 onto itself is inhibitory, due to the complex formation. In Fig. 14(ii), the upper plot shows the steady states of the value of the control  $p_3$  as a function of the input  $p_1$ . A supercritical Hopf bifurcation is seen to occur at  $p_1 \simeq 2.5$ . Fig. 14(ii) lower right-hand plot shows steady oscillations of  $p_3$ . The oscillations arise due to the gate properties of G1. Initially, when the system is at steady state, and the inputs  $p_1$  and  $p_2$  are fixed,  $p_3$  has a small value which makes G1 behave as an **AND** gate. since both inputs are present, the output  $p_5$  is high. There is thus considerable sequestration of  $p_4$  due to the complex formation. This implies a reduced production of  $p_3$ , which is consistent with G1 being in the **AND** state. Now if one of the inputs to the system is removed (*e.g* by making  $p_1$  decay), since initially the gate is in the **AND** state, the output  $p_5$  decreases. This results in the release of  $p_4$ , which begins increasing the transcription of G3; then  $p_3$  increases, and the gate G1 switches to the **OR** state. But in this state, G1 can be transcribed by  $p_2$ , and the output  $p_5$  increases. This once again results in sequestration of  $p_4$ , and finally reduces the control  $p_3$ , and in this way we complete one cycle. The system therefore switches back and forth between the two states and hence this leads to oscillations.

We now describe another application of an adjustable gate. However in this case, the gate properties are reversed, i.e., the gate implements an **OR** gate for low input control transcription factor concentration, and an **AND** gate for high input control transcription factor concentration. We discuss the nature of the regulation and its consequences without simulations, since this case is very similar to the previously described model. For this case we assume the following regulatory rules: all three transcription factors and RNAP bind to the gene; each of the transcription factors  $p_1, p_2$  and RNAP bind individually to the gene; and the complex  $p_1 p_2$  and RNAP can bind to the gene. These assumptions lead to the following rate law,

$$T = \frac{s_1 p_1 p_2 + s_2 p_1 + s_3 p_2 + s_4 p_1 p_2 p_3}{1 + s_5 p_1 + s_6 p_2 + s_7 p_3 + s_8 p_1 p_2 + s_9 p_1 p_3 + s_{10} p_2 p_3 + s_{11} p_1 p_2 p_3} \quad (16)$$

By inspection it is clear that for low  $p_3$ , G1 behaves like an **OR** gate with respect to  $p_1$  and  $p_2$ , whereas for high  $p_3$ , it behaves like an **AND** gate. If we now consider the same network as described above but substitute this motif into G1, then the system shows an almost homeostatic behavior with respect to a change in its input. This is easy to understand since initially, when both inputs are present, the output  $p_5$  must be large. Due to the nature of the feedback, this determines the value of  $p_3$  to be at a low level. The system is therefore initially in the **OR** state. If now one of the inputs is suddenly decreased, since the system is initially in an **OR** state, the output would continue to be high. There would be a small transient due to the sudden change in input, but the system would reach a steady state as before. This then allows this network to be fairly unperturbed to changes in one of its input transcription factors.

What could be the function of such networks with adjustable gates? In the first case (with **AND** gate properties for low  $p_3$ ), a sudden drop in a transcription factor concentration could set up oscillatory patterns in the network which would then signal the next program to be carried out by the genetic network. In the second case (with the gate properties reversed), it is clearly useful to have a homeostatic network which works in such a way so as to counteract any sudden changes in input transcription factor concentration levels.

Although we have not found explicit examples for many of the networks we have discussed, which display such complex behavior, we believe that such an endeavor is worth exploring.

## Conclusions

As a first step towards recognizing and understanding large complicated pathways, we have discussed in this work the modular design of several functional network motifs. Each of the networks consists of genes

which are regulated by multiple transcription factors. The combinatorial regulation was explored in each case, and the networks which emerged were found to have very distinct properties. Our modeling procedure used the Shea-Ackers method [21], which allowed us to derive the rates of transcription which were then used to explore the network dynamics. The networks could broadly be classified into: networks which are derived from incoherent feedforward motifs; and networks which can change their gating properties based upon an external input.

We first discussed the steady state properties of feedforward networks, which can be used as amplitude filters. We found that both the Type I simple and mixed feedforward networks led to a similar design, i.e. filtering out the input transcription factor concentration, although both networks worked through different types of interactions. Furthermore, we discussed the effects of dimerization for a simple Type I feedforward, which has the effect of narrowing the bandwidth of the amplitude filter. To study the filter characteristics of these networks, we simulated the effects of mutations which would change the protein-DNA binding strengths. These generally have the effect of shifting the amplitude filter curve and modulating its bandwidth. Furthermore we described how these motifs can be applied to a biological setting. By having a common transcription factor as the input to two amplitude filter modules, but with shifted filter characteristics, it was possible to obtain a time ordered response of protein production. Homeostatic networks emerged if the output of the amplitude filter was fed back to itself. This network was found to be resilient in its output to either increasing or decreasing values of an external input transcription factor, depending on whether the feedback was assumed to be positive or negative respectively.

We next described a tunable motif network, where the regulation at one of the genes made it possible for the networks to exhibit bistability or oscillatory behavior if one of the external input transcription factor concentration was made to increase/decrease respectively. Finally we discussed gate properties of regulation at a gene, which can be made to switch between an **AND/OR** depending on the one of the input transcription factor concentrations.

## Methods

### Simulations

All simulations were carried out using the Systems Biology Workbench (SBW) tools [47]: the network designer, JDesigner, the simulation engine Jarnac [48]. Bifurcation diagrams were computed using SBW with an interface to MATLAB [49], and a bifurcation discovery tool [50]. Bifurcation plots were also



computed and cross checked using Oscill8 <sup>1</sup>, an interactive bifurcation software package which is linked to AUTO [51], and SBW [47]. In all our simulations the species concentrations are regarded as dimensionless, whereas the kinetic constants have dimensions of inverse time, with dimensionless Michaelis-Menten constants. All models are available as Jarnac scripts (supplied in the supplement) which can be easily translated to SBML [52] using the JarnacLite tool that is part of the SBW suite [47].

## Author contributions

HS helped conceive and fund the project; SY contributed to manuscript preparation and final data analysis.

## Acknowledgements

This work was supported by grants from the National Science Foundation (0432190 and FIBR 0527023) to HMS. The authors wish to thank Carsten Peterson for useful discussions and most significantly to Vijay Chickarmane for technical assistance in carrying out the simulations and deriving the transcription factor binding kinetics. VC declined to be a co-author on the manuscript but was also supported by NSF FIBR 0527023.

## References

1. Milo R, Shen-Orr SS, Itzkovitz S, Kashtan N, Chklovskii D, Alon U: **Network motifs: simple building blocks of complex networks**. *Science* 2002, **298**(5594):824–827.
2. Lee TI, Rinaldi NJ, Robert F, Odom DT, Bar-Joseph Z, Gerber G, Hannett NM, Harbison CT, Thompson CM, Simon I, et al: **Transcriptional regulatory networks in *Saccharomyces cerevisiae***. *Science* 2002, **298**(5594):799–804.
3. Shen-Orr SS, Milo R, Mangan S, Alon U: **Network motifs in the transcriptional regulation network of *Escherichia coli***. *Nat Genet* 2002, **31**:64–68.
4. Yeger-Lotem Y, Sattath S, Kashtan N, Itzkovitz S, Milo R, Pinter RY, Alon U, Margalit H: **Network motifs in integrated cellular networks of transcription-regulation and protein-protein interaction**. *Proc Natl Acad Sci U S A* 2004, **101**(16):5934–5939.
5. Krogan NJ, Cagney G, Yu H, Zhong G, Guo X, Ignatchenko A, Li J, Pu S, Datta N, Tikuisis AP, et al: **Global landscape of protein complexes in the yeast *Saccharomyces cerevisiae***. *Nature* 2006, **440**(7084):637–643.
6. Mangan S, Alon U: **Structure and function of the feed-forward loop network motif**. *Proc Natl Acad Sci U S A* 2003, **100**(21):11980–11985.
7. Mangan S, Zaslaver A, Alon U: **The coherent feedforward loop serves as a sign-sensitive delay element in transcription networks**. *J Mol Biol* 2003, **334**(2):197–204.
8. Kalir S, Mangan S, Alon U: **A coherent feed-forward loop with a sum input function prolongs flagella expression in *Escherichia coli***. *Mol Syst Biol* 2005, **1**:2005.0006.

---

<sup>1</sup><http://sourceforge.net/projects/oscill8>

9. Mangan S, Itzkovitz S, Zaslaver A, Alon U: **The incoherent feed-forward loop accelerates the response-time of the gal system of Escherichia coli.** *J Mol Biol* 2006, **356**(5):1073–1081.
10. Guido NJ, Wang X, Adalsteinsson D, McMillen D, Hasty J, Cantor CR, Elston TC, Collins JJ: **A bottom-up approach to gene regulation.** *Nature* 2006, **439**(7078):856–860.
11. Andrianantoandro E, Basu S, Karig DK, Weiss R: **Synthetic biology: new engineering rules for an emerging discipline.** *Mol Syst Biol* 2006, **2**:2006.0028.
12. Kaern M, Weiss R: **Synthetic gene regulatory systems.** In *System Modeling in Cellular Biology: From Concepts to Nuts and Bolts*. Edited by Szallasi Z, Stelling J, Periwé V, MIT Press 2006:269–298.
13. Bolouri H, Davidson EH: **Modeling transcriptional regulatory networks.** *BioEssays* 2002, **24**(12):1118–1129.
14. Kaern M, Blake WJ, Collins JJ: **The engineering of gene regulatory networks.** *Annu Rev Biomed Eng* 2003, **5**:179–206.
15. Lahav G, Rosenfeld N, Sigal A, Geva-Zatorsky N, Levine AJ, Elowitz MB, Alon U: **Dynamics of the p53-mdm2 feedback loop in individual cells.** *Nat Genet* 2004, **36**(2):147–150.
16. Geva-Zatorsky N, Rosenfeld N, Itzkovitz S, Milo R, Sigal A, Dekel E, Yarnitzky T, Liron Y, Polak P, Lahav G, Alon U: **Oscillations and variability in the p53 system.** *Mol Syst Biol* 2006, **2**:2006.0033.
17. Ptashne M, Gunn A: *Genes and Signals*. New York: Cold Spring Harbor Laboratory Press 2001.
18. Bintu L, Buchler NE, Garcia HG, Gerland U, Hwa T, Kondev J, Kuhlman T, Phillips R: **Transcriptional regulation by the numbers: applications.** *Curr Opin Genet Dev* 2005, **15**(2):125–135.
19. Buchler NE, Gerland U, Hwa T: **On schemes of combinatorial transcription logic.** *Proc Natl Acad Sci U S A* 2003, **100**(9):5136–5141.
20. Ackers GK, Johnson AD, Shea MA: **Quantitative model for gene regulation by lambda phage repressor.** *Proc Natl Acad Sci U S A* 1982, **79**(4):1129–1133.
21. Bintu L, Buchler NE, Garcia HG, Gerland U, Hwa T, Kondev J, Phillips R: **Transcriptional regulation by the numbers: models.** *Curr Opin Genet Dev* 2005, **15**(2):116–124.
22. Hill T: *Introduction to Statistical Thermodynamics*. Massachusetts, USA: Addison-Wesley 1960.
23. Kepler TB, Elston TC: **Stochasticity in transcriptional regulation: origins, consequences, and mathematical representations.** *Biophys J* 2001, **81**(6):3116–3136.
24. Hornos JE, Schultz D, Innocentini GC, Wang J, Walczak AM, Onuchic JN, Wolynes PG: **Self-regulating gene: an exact solution.** *Phys Rev E* 2005, **72**(5 Pt 1):051907.
25. Kaern M, Elston TC, Blake WJ, Collins JJ: **Stochasticity in gene expression: from theories to phenotypes.** *Nat Rev Genet* 2005, **6**(6):451–464.
26. McAdams HH, Arkin A: **Simulation of prokaryotic genetic circuits.** *Annu Rev Biophys Biomol Struct* 1998, **27**:199–224.
27. Ishihara S, Fujimoto K, Shibata T: **Cross talking of network motifs in gene regulation that generates temporal pulses and spatial stripes.** *Genes Cells* 2005, **10**(11):1025–1038.
28. Basu S, Mehreja R, Thiberge S, Chen MT, Weiss R: **Spatiotemporal control of gene expression with pulse-generating networks.** *Proc Natl Acad Sci USA* 2004, **101**(17):6355–6360.
29. Basu S, Gerchman Y, Collins CH, Arnold FH, Weiss R: **A synthetic multicellular system for programmed pattern formation.** *Nature* 2005, **434**(7037):1130–1134.
30. Wolf DM, Arkin AP: **Motifs, modules and games in bacteria.** *Curr Opin Microbiol* 2003, **6**(2):125–134.
31. Mayya V, Loew LM: **STAT module can function as a biphasic amplitude filter.** *IEE Proc. Systems Biology* 2005, **2**:43–52.
32. Bundschuh R, Hayot F, Jayaprakash C: **The role of dimerization in noise reduction of simple genetic networks.** *J Theor Biol* 2003, **220**(2):261–269.
33. Alberts B, Bray D, Hopkin K, Johnson A, Lewis J, Raff M, Roberts K, Walter P: *Essential Cell Biology*. New York: Taylor & Francis Group, 2nd edition 2003.

34. Kashtan N, Itzkovitz S, Milo R, , Alon U: **Topological generalizations of network motifs.** *Phys Rev E* 2004, **70**(3 Pt 1):031909.
35. Kalir S, McClure J, Pabbaraju K, Southward C, Ronen M, Leibler S, Surette MG, Alon U: **Ordering genes in a flagella pathway by analysis of expression kinetics from living bacteria.** *Science* 2001, **292**(5524):2080–2083.
36. Eichenberger P, Fujita M, Jensen ST, Conlon EM, Rudner DZ, Wang ST, Ferguson C, Haga K, Sato T, Liu JS, Losick R: **The program of gene transcription for a single differentiating cell type during sporulation in *Bacillus subtilis*.** *PLoS Biol* 2004, **2**(10):e328.
37. Yi TM, Huang Y, Simon MT, Doyle J: **Robust perfect adaptation in bacterial chemotaxis through integral feedback control.** *Proc Natl Acad Sci U S A* 2000, **97**(9):4649–4653.
38. Voigt CA, Wolf DM, P AA: **The bacillus subtilis sin operon: an evolvable network motif.** *Genetics* 2005, **169**(3):1187–1202.
39. Atkinson MR, Savageau MA, Myers JT, Ninfa AJ: **Development of genetic circuitry exhibiting toggle switch or oscillatory behavior in *Escherichia coli*.** *Cell* 2003, **113**(5):597–607.
40. Gardner TS, Cantor CR, Collins JJ: **Construction of a genetic toggle switch in *Escherichia coli*.** *Nature* 2000, **403**(6767):339–342.
41. Becskei A, Seraphin B, Serrano L: **Positive feedback in eukaryotic gene networks: cell differentiation by graded to binary response conversion.** *EMBO J* 2001, **20**(10):2528–2535.
42. Elowitz MB, Leibler S: **A synthetic oscillatory network of transcriptional regulators.** *Nature* 2000, **403**(6767):335–338.
43. Hasty J, Isaacs F, Dolnik M, McMillen D, Collins JJ: **Designer gene networks: Towards fundamental cellular control.** *Chaos* 2001, **11**:207–220.
44. SStrogatz: *Nonlinear Dynamics and Chaos*. USA: Westview Press 1994.
45. Kuznetsov YA: *Elements of applied bifurcation theory*. New York: Springer-Verlag 1995.
46. Setty Y, Mayo AE, Surette MG, Alon U: **Detailed map of a cis-regulatory input function.** *Proc Natl Acad Sci U S A* 2003, **100**(13):7702–7707.
47. Sauro HM, Hucka M, Finney A, Wellock C, Bolouri H, Doyle J, Kitano H: **Next generation simulation tools: The systems biology workbench and biospice integration.** *OMICS* 2003, **7**(4):355–372.
48. Sauro HM: **Jarnac: A system for interactive metabolic analysis.** In *Animating the Cellular Map: Proceedings of the 9th International Meeting on BioThermoKinetics*. Edited by Hofmeyr JHS, Rohwer JM, Snoep JL 2000.
49. Wellock C, Chickarmane V, Sauro HM: **The sbw-matlab interface.** *Bioinformatics* 2005, **21**(6):823–824.
50. Chickarmane V, Paladugu SR, Bergmann F, Sauro HM: **Bifurcation discovery tool.** *Bioinformatics* 2005, **21**(18):3688–3690.
51. Doedel EJ: **Auto: a program for the automatic bifurcation analysis of autonomous systems.** In *Proc. Manitoba Conf. Num. Math. Comput., 10th, Winnipeg, Canada, Congressus Numeratum* 1981:265–284.
52. Hucka M, et al: **The Systems Biology Markup Language (SBML): A medium for representation and exchange of biochemical network models.** *Bioinformatics* 2003, **19**(4):524–531.

## Figures

**Figure 1 - Feedforward motifs extracted from analyzing**

protein-protein and protein-DNA interaction databases. (a) Simple feedforward, the thin arrows indicate transcriptional activity, (b) Mixed feedforward; In addition to the transcriptional activity, the thick arrow indicates a protein interaction.

**Figure 2 - Interpretations of the feedforward motifs shown in Fig. 1(b) in terms of a reaction network.**

$p_1$  is the input to the system comprising of genes G1 and G2. G1 produces  $p_2$ , and G2,  $p_3$ ,  $p_1$  activates G2,  $p_2$  represses G2. The line which ends with a dot represents activation, and the line which ends with a small line perpendicular to it represents repression.

**Figure 3 - Steady state values of  $p_3$ , and  $p_2$  for the simple incoherent Type I feedforward network as a function of the input factor  $p_1$**

**Figure 4 - Steady state value of  $p_3$  as a function of  $p_1$  for the simple feedforward with dimerization, and for the consequences of mutations at G1 and G2.**

Upper plot: The effects of dimerization in a simple feedforward, as compared to a curve obtained for a simple feedforward network. Lower Plots: (a)  $p_3$  as a function of  $p_1$  for wild (strong binding of  $p_1$  to G1) and mutant types (weak binding of  $p_1$  to G1). (b)  $p_3$  as a function of  $p_1$  for wild (strong binding of  $p_1p_2$  to G2) and mutant types (weak binding of  $p_1p_2$  to G2).

**Figure 5 - Time ordered production of proteins can be achieved by feeding in a common input into two or more amplitude filter modules that have different maximal responses.**

**Figure 6 - Sample figure title**

(a): Steady state values of the amplitude filter outputs as a function of the input A, showing the shifted output peaks with respect to the input transcription factor concentration. (b): The amplitude filter outputs as a function of time showing the time ordering.

**Figure 7 - Homeostatic networks built out of the amplitude filter motifs.**

(a) Feedback,  $p_3$  from the output amplitude filter positively regulates gene G1, (b) Feedback,  $p_3$  from the output amplitude filter negatively regulates gene G1.

**Figure 8 - Homeostatic networks built out of the amplitude filter motifs.**

(a): Steady state values of  $p_3$  as a function of the input A. (b):  $p_3$ ,  $p_1$  and the input A as a function of time.

**Figure 9 - Interpretations of the second feedforward motifs shown in Fig. 1 in terms of a reaction network.**

$p_1$  degrades  $p_2$  via a binding reaction, at G2,  $p_2$  activates G2, whereas  $p_1$  acts as a repressor.

**Figure 10 - Steady State response of a mixed feedforward network as a function of input factor  $p_1$ .**

**Figure 11 - A cartoon of the tunable motif which shows three interacting genes: G1, G2 and G3, and their gene products  $p_1, p_2, p_3$  respectively.**

Regulation at G1 includes positive regulation by an external transcription factor A and  $p_3$ , and repression by  $p_2$ . The transcription factor A for large concentrations can out compete  $p_3$  in binding to G1. The effect of this is to break the feedback between the two antagonists which make up the toggle switch, and hence the network exhibits bistability for large A.

**Figure 12 - Bifurcation diagram and time-series plots for the tunable motifs.**

The left figure shows the bifurcation plot for the steady state value of  $p_1$ , as a function of the transcription factor concentration A. A subcritical bifurcation occurs at  $A \sim 9$ , and oscillations occur for  $A \leq 11$ . At  $A \sim 35$ , a saddle-node bifurcation occurs which gives rise to the appearance of two stable steady states.

Figure (a) shows time series plots for  $p_1, p_2, p_3$ , which show oscillations, for the case where  $A = 1$ . Figure (b) shows the final steady state of  $p_1$  reaching either of two values, depending on the initial conditions.

This is due to the bistable behavior of the circuit. The parameter for this case is  $A = 50$

**Figure 13 - The figures show the transcription rate as a function of the transcription factor concentrations,  $p_1, p_2$ , for fixed values of the control transcription factor  $p_3$ .**

(a),  $p_3 = 1$ , represents an **AND** gate, (b),  $p_3 = 10$ , represents an **OR** gate.

**Figure 14 - An application of adjustable gates**

Panel (i) shows the schematic of the network while Panel (ii) shows the simulations results. In (ii), the upper plot shows the bifurcation plot of  $p_3$ , as a function of the input  $p_1$ . A supercritical Hopf bifurcation is seen to occur at  $p_1 \simeq 2.5$ . The lower panel in (ii)(a) shows the decay of  $p_1$ , while the lower panel in (ii)(b) shows the system reaching steady oscillations of  $p_3$ , after an initial transient.

**Figure 15 - A logical diagram of the schematic shown in Fig. 14.**

The triangle symbol represents a Boolean inverter. The action of the Boolean gate switches the AND-OR gate between AND and OR functions

## A Appendix 1

In this section we demonstrate the equivalence of the thermodynamic (Shea-Ackers) approach with that of the enzyme kinetic approach to derive the equations for the feedforward network. Although this is well known we provide this derivation explicitly to show how a particular choice of interaction can be used to determine a reaction scheme. The reaction scheme is required if a stochastic simulation is to be performed. From Fig. 2 we see that  $p_1$  is an activator for G1. RNAP can also bind to G1 in the absence of  $p_1$ , but at a lower rate. As described in the main text, such binding leads to “leaky transcription”. At the operator sites of G2,  $p_1$  can bind and recruit RNAP to the operator site of the gene. However,  $p_1$  also recruits  $p_2$ , the gene product of G1, and in this state, transcription is repressed. We also assume that  $p_2$  binding to G2, occurs only as recruitment, and cannot occur by itself. From these assumptions, we can draw up the following truth tables for the transcriptional regulation at G1 and G2.

| $p_1$ | $P$ | Rate              |
|-------|-----|-------------------|
| 0     | 0   | 1                 |
| 1     | 0   | $\alpha_1[p_1]$   |
| 0     | 1   | $\alpha_2[P]$     |
| 1     | 1   | $\alpha_3[p_1 P]$ |

| $p_1$ | $p_2$ | $P$ | Rate                |
|-------|-------|-----|---------------------|
| 0     | 0     | 0   | 1                   |
| 0     | 1     | 0   | $\times$            |
| 1     | 0     | 0   | $\beta_2[p_1]$      |
| 1     | 1     | 0   | $\beta_3[p_1][p_2]$ |
| 0     | 0     | 1   | $\beta_4[P]$        |
| 0     | 1     | 1   | $\times$            |
| 1     | 0     | 1   | $\beta_6[p_1][P]$   |
| 1     | 1     | 1   | $\times$            |

Table 1: Logic for the transcriptional regulation underlying simple feedforward genes. In the case where transcription is unlikely to occur the rate is denoted by  $\times$  and assigned to zero in the calculations.

In the above table and the subsequent tables the terms  $\alpha_i, \beta_i$ , are related to the free energies of binding through  $\exp \frac{\delta G}{k_B T}$ . The logic in Table 1 can be translated to the rate of transcription by computing the fractional probability of each of the genes G1 and G2 being bound by RNAP. The transcription rates,  $Tr_{G1}, Tr_{G2}$ , are proportional to the probability of occupancy of RNAP, which can be computed from the above two tables to be,

$$Tr_{G1} \propto \frac{\alpha_1 [P] + \alpha_3 [p_1] [P]}{1 + \alpha_1 [P] + \alpha_2 [p_1] + \alpha_3 [p_1] [P]} \quad (17)$$

---

|               |                      |                |                      |
|---------------|----------------------|----------------|----------------------|
| $p_1 + G1$    | $\rightleftharpoons$ | $G1p_1$        | $(k_{1f}, k_{1b})$   |
| $P + G1$      | $\rightleftharpoons$ | $G1P$          | $(k_{1pf}, k_{1pb})$ |
| $P + G1p_1$   | $\rightleftharpoons$ | $G1p_1P$       | $(k_{2pf}, k_{2pb})$ |
| $G1P$         | $\rightarrow$        | $G1P + p_2$    | $(k_{p_2})$          |
| $G1p_1P$      | $\rightarrow$        | $G1p_1P + p_2$ | $(k_{p_2})$          |
| $p_2$         | $\rightarrow$        | $\phi$         | $(\gamma_2)$         |
| $p_1 + G2$    | $\rightleftharpoons$ | $G2p_1$        | $(k_{3f}, k_{3b})$   |
| $G2p_1 + p_2$ | $\rightleftharpoons$ | $G2p_1p_2$     | $(k_{4f}, k_{4b})$   |
| $P + G2p_1$   | $\rightleftharpoons$ | $G2p_1P$       | $(k_{3pf}, k_{3pb})$ |
| $P + G2$      | $\rightleftharpoons$ | $G2P$          | $(k_{4pf}, k_{4pb})$ |
| $G2P$         | $\rightarrow$        | $G2P + p_3$    | $(k_{p_3})$          |
| $G2p_1P$      | $\rightarrow$        | $G2p_1P + p_3$ | $(k_{p_4})$          |
| $p_3$         | $\rightarrow$        | $\phi$         | $(\gamma_3)$         |

---

Table 2: Reaction Scheme for the feedforward network.

$$Tr_{G2} \propto \frac{\beta_4 [P] + \beta_6 [p_1] [P]}{1 + \beta_4 [P] + \beta_2 [p_1] + \beta_3 [p_1] [p_2] + \beta_6 [p_1] [P]}$$

The transcription rates are then used in the rate laws described in Eq. 4. We now compute the above result using the reaction kinetics approach. Assume that for the gene G1, there are 4 states: G1-unbound or free,  $G1p_1$ -bound by  $p_1$ ,  $G1P$ -bound by RNAP,  $G1p_1P$ -bound by  $p_1$  and RNAP. Then it follows that,

$$[G1] + [G1p_1] + [G1P] + [G1p_1P] = 1. \quad (18)$$

For gene G2, there are 5 states: G2-unbound or free,  $G2p_1$ -bound by  $p_1$ ,  $G2P$ -bound by RNAP,  $G2p_1p_2$ -bound by  $p_1$  and  $p_2$  and  $G2p_1P$ -bound by  $p_1$  and RNAP, which leads to,

$$[G2] + [G2p_1] + [G2P] + [G1p_1P] + [G1p_1p_2] = 1. \quad (19)$$

The following reaction scheme defines the network, From the above reaction scheme, we obtain at thermodynamic equilibrium,

$$\begin{aligned} [G1p_1] &= k_1 [p_1] [G1], [G1p_1P] = k_{2p} [G1p_1] [P], [G1P] = k_{1p} [G1] [P] \\ [G2p_1] &= k_3 [G2] [p_1], [G2p_1p_2] = k_4 [G2p_1] [p_2], [G2P] = k_{4p} [G2] [P], \\ [G2p_1P] &= k_{4p} [G2p_1] [P] \end{aligned} \quad (20)$$

where in the above equations we use the equilibrium constants, which are ratios of the forward to backward rates, *e.g*  $k_1 = \frac{k_{1f}}{k_{1b}}$ , *etc.* Using Eqns. 17, 18 & 19, the ratio of genes bound by RNAP, and hence the transcription rates can be evaluated to be,

$$\begin{aligned} Tr_{G1} &\propto \frac{k_{1p} P + k_1 k_{2p} p_1 P}{1 + k_1 p_1 + k_1 k_{2p} p_1 P + k_{1p} P} \\ Tr_{G2} &\propto \frac{k_{3p} P + k_2 k_{4p} p_1 P}{1 + k_{3p} P + k_2 p_1 + k_1 k_3 p_1 p_2 + k_2 k_{4p} p_1 P} \end{aligned} \quad (21)$$

which is functionally the same in form to Eq. 17. Both methods are equivalent as the only physical requirement is thermal equilibrium for these reactions. Although the statistical approach is more intuitive, the equilibrium approach allows us to define a reaction scheme, which can be described in terms of measurable kinetic constants.

## B Appendix 2

In each of the subsections below, the transcriptional rates for the genes, which are described by the truth table for the transcriptional rules, are derived. The parameter values used for the simulations are also provided. The parameters used in the equations are lumped, in the sense that we group together terms which depend on the same variable, *e.g*  $\alpha_3 [p_1] [P] + \alpha_2 [p_1] = v_1 p_1$  *etc.* We also assume for simplicity that  $P = 1$ .

### B.1 Feedforward Networks

#### B.1.1 Simple Feedforward

Table 1, in Appendix I describes the regulation at G1 and G2. The parameter values used in Eq. 4 are,

| $a_1$ | $a_2$ | $a_3$ | $a_4$ | $\gamma_1$ | $b_1$ | $b_2$ | $b_3$ | $b_4$ | $b_5$             | $\gamma_2$ |
|-------|-------|-------|-------|------------|-------|-------|-------|-------|-------------------|------------|
| 0     | 0.01  | 0     | 0.002 | 0.01       | 0     | 1     | 0     | 0.011 | $3 \cdot 10^{-4}$ | 0.08       |

Table 3: Parameters values for Eq. 4.

#### B.1.2 Mixed Feedforward

$$Tr_{G1} \propto \frac{\delta_2 [P] + \delta_3 [p_1] [P]}{1 + \delta_2 [P] + \delta_1 [p_1] + \delta_3 [p_1] [P]} \quad (22)$$



| $p_1$ | $P$ | Rate              |
|-------|-----|-------------------|
| 0     | 0   | 1                 |
| 1     | 0   | $\delta_1[p_1]$   |
| 0     | 1   | $\delta_2[P]$     |
| 1     | 1   | $\delta_3[p_1 P]$ |

| $p_1$ | $p_2$ | $P$ | Rate                   |
|-------|-------|-----|------------------------|
| 0     | 0     | 0   | 1                      |
| 0     | 1     | 0   | $\epsilon_1[p_2]$      |
| 1     | 0     | 0   | $\epsilon_2[p_1]$      |
| 1     | 1     | 0   | $\epsilon_3[p_1][p_2]$ |
| 0     | 0     | 1   | $\epsilon_4[P]$        |
| 0     | 1     | 1   | $\epsilon_5[p_2][P]$   |
| 1     | 0     | 1   | $\times$               |
| 1     | 1     | 1   | $\times$               |

Table 4: Logic for the transcriptional regulation underlying mixed feedforward network genes, Eq. 7.

$$Tr_{G2} \propto \frac{\epsilon_4 [P] + \epsilon_5 [p_2] [P]}{1 + \epsilon_4 [P] + \epsilon_1 [p_2] + \epsilon_2 [p_1] + \epsilon_3 [p_1] [p_2] + \epsilon_5 [p_2] [P]}$$

| $c_1$ | $c_2$ | $c_3$ | $c_4$ | $\gamma_c$ | $\gamma_1$ | $d_1$ | $d_2$ | $d_3$ | $d_4$ | $d_5$  | $d_6$     | $\gamma_2$ |
|-------|-------|-------|-------|------------|------------|-------|-------|-------|-------|--------|-----------|------------|
| 0     | 0.01  | 0     | 0.002 | 0.0001     | 0.01       | 0     | 0.5   | 0     | 0.001 | 0.0051 | $10^{-4}$ | 0.09       |

Table 5: Parameters values for Eq. 7.

### B.1.3 Consequence of Dimerization for a Simple Feedforward and the effects of Mutations at G1, G2.

| $e_1$ | $e_2$ | $e_3$ | $e_4$ | $\gamma_1$ | $k_{d1}$ | $k_{d2}$ | $k_{d3}$ | $d_1$ | $d_2$ | $d_3$ | $d_4$ | $d_5$ | $\gamma_2$ |
|-------|-------|-------|-------|------------|----------|----------|----------|-------|-------|-------|-------|-------|------------|
| 0     | 0.01  | 0     | 0.002 | 0.01       | 20       | 2000     | 0.001    | 0     | 1     | 0     | .011  | 0.003 | 0.08       |

Table 6: Parameters values for Eq. 6.

The upper plot in Fig 4, for the simple feedforward (monomer) we used the same parameters values as in Table3. For the lower two figures, the mutations were carried on the parameters  $e_2, d_5$ . Their values are given by, panel A:  $e_2 = 0.001$ -wild type,  $e_2 = 2 \times 10^{-4}$ -mutant, panel B:  $d_5 = 0.003$ -wild type,  $d_5 = 5 \times 10^{-5}$ -mutant

### B.1.4 Application 1: Time Ordering

The amplitude filter parameters used for the simulations in Fig. 6 are the same as in Table 3, except for the following changes given by,

| Filter # | $e_2$             | $d_5$             | $\gamma_2$ |
|----------|-------------------|-------------------|------------|
| 1        | 0.001             | 0.05              | 0.07       |
| 2        | $5 \cdot 10^{-4}$ | $5 \cdot 10^{-4}$ | 0.3        |

Table 7: Parameters values for Fig. 6.

### B.1.5 Application 2: Homeostatic Networks

The regulation at G1 in Fig. 7 (a) is assumed to be,

| $A$ | $p_3$ | $P$ | Rate                |
|-----|-------|-----|---------------------|
| 0   | 0     | 0   | 1                   |
| 1   | 0     | 0   | $\rho_1[A]$         |
| 0   | 1     | 0   | $\rho_2[p_3]$       |
| 1   | 1     | 0   | $\rho_3[A][p_3]$    |
| 0   | 0     | 1   | $\rho_4[P]$         |
| 1   | 0     | 1   | $\times$            |
| 0   | 1     | 1   | $\times$            |
| 1   | 1     | 1   | $\rho_7[A][p_3][P]$ |

Table 8: Logic for the transcriptional regulation underlying G1 for the homeostatic network.

$$Tr_{G1} \propto \frac{\rho_4[P] + \rho_7[A][p_3][P]}{1 + \rho_1[A] + \rho_2[p_3] + \rho_3[A][p_3] + \rho_4[P] + \rho_7[A][p_3][P]} \quad (23)$$

The parameter values used in Eq. 8, to generate Fig. 8 are given by, and the parameters used for the

| $u_1$ | $u_2$ | $u_3$ | $u_4$ | $u_5$ | $u_6$ | $\gamma_1$ |
|-------|-------|-------|-------|-------|-------|------------|
| 0     | 100   | 0     | 0.01  | 0.001 | 11    | 0.1        |

Table 9: Parameters values for Eq. 7.

amplitude filter are the same as in Table 4.

## B.2 Tunable Motifs

$$\begin{aligned}
Tr_{G1} &\propto \frac{\varepsilon_6[A][P] + \varepsilon_7[p_3][P]}{1 + \varepsilon_1[A] + \varepsilon_2[p_2^4] + \varepsilon_3[A][p_2^4] + \varepsilon_4[p_3] + \varepsilon_5[p_2^4][p_3] + \varepsilon_6[A][P] + \varepsilon_7[p_3][P]} \\
Tr_{G2} &\propto \frac{\zeta_2[P]}{1 + \zeta_2[P] + \zeta_1[p_1^4]} \\
Tr_{G3} &\propto \frac{\eta_2[P] + \eta_3[p_2][P]}{1 + \eta_1[p_2] + \eta_2[P] + \eta_3[p_2][P]}
\end{aligned} \quad (24)$$

The parameter values in Eq. 8, are given by,

| $A$ | $p_1$ | $p_2^4$ | $p_3$ | $P$ | Rate                        |
|-----|-------|---------|-------|-----|-----------------------------|
| 0   | 0     | 0       | 0     | 0   | 1                           |
| 1   | 0     | 0       | 0     | 0   | $\varepsilon_1[A]$          |
| 0   | 0     | 1       | 0     | 0   | $\varepsilon_2[p_2^4]$      |
| 1   | 0     | 1       | 0     | 0   | $\varepsilon_3[A][p_2^4]$   |
| 0   | 0     | 0       | 1     | 0   | $\varepsilon_4[p_3]$        |
| 0   | 0     | 1       | 1     | 0   | $\varepsilon_5[p_2^4][p_3]$ |
| 1   | 0     | 0       | 0     | 1   | $\varepsilon_6[A][P]$       |
| 0   | 0     | 0       | 1     | 1   | $\varepsilon_7[p_3][P]$     |

| $p_1^4$ | $P$ | Rate             | $p_2$ | $P$ | Rate             |
|---------|-----|------------------|-------|-----|------------------|
| 0       | 0   | 1                | 0     | 0   | 1                |
| 1       | 0   | $\zeta_1[p_1^4]$ | 1     | 0   | $\eta_1[p_1]$    |
| 0       | 1   | $\zeta_2[P]$     | 0     | 1   | $\eta_2[P]$      |
| 1       | 1   | $\times$         | 1     | 1   | $\eta_3[p_1][P]$ |

Table 10: Logic for the transcriptional regulation underlying the Tunable Motif network genes, for G1, G2 and G3 respectively.

| $m_1$             | $m_2$ | $m_3$      | $m_4$ | $m_5$ | $m_6$ | $m_7$ | $\gamma_1$ | $n_1$ |
|-------------------|-------|------------|-------|-------|-------|-------|------------|-------|
| $2 \cdot 10^{-3}$ | 0.2   | 0.01       | 1     | 0.01  | 0.01  | 0.01  | 0.1        | 0.15  |
| $n_2$             | $n_3$ | $\gamma_2$ | $o_1$ | $o_2$ | $o_3$ | $o_4$ | $\gamma_2$ |       |
| 0.001             | 1     | .1         | 0     | 0.01  | 0     | 0.001 | 0.01       |       |

Table 11: Parameters values for Eq. 8.

### B.3 Adjustable Gates

| $p_1$ | $p_2$ | $p_3$ | $P$ | Rate                       |
|-------|-------|-------|-----|----------------------------|
| 0     | 0     | 0     | 0   | 1                          |
| 1     | 0     | 0     | 0   | $\theta_1[p_1]$            |
| 0     | 1     | 0     | 0   | $\theta_2[p_2]$            |
| 0     | 0     | 1     | 0   | $\theta_3[p_3]$            |
| 1     | 0     | 1     | 0   | $\theta_4[p_1][p_3]$       |
| 0     | 1     | 1     | 0   | $\theta_5[p_2][p_3]$       |
| 1     | 1     | 0     | 0   | $\theta_6[p_1][p_2]$       |
| 1     | 1     | 1     | 0   | $\theta_7[p_1][p_2][p_3]$  |
| 1     | 0     | 1     | 1   | $\theta_8[p_1][p_3][P]$    |
| 0     | 1     | 1     | 1   | $\theta_9[p_2][p_3][P]$    |
| 1     | 1     | 0     | 1   | $\theta_{10}[p_1][p_2][P]$ |

| $p_1$ | $p_2$ | $p_3$ | $P$ | Rate                               |
|-------|-------|-------|-----|------------------------------------|
| 0     | 0     | 0     | 0   | 1                                  |
| 1     | 0     | 0     | 0   | $\vartheta_1[p_1]$                 |
| 0     | 1     | 0     | 0   | $\vartheta_2[p_2]$                 |
| 0     | 0     | 1     | 0   | $\vartheta_3[p_3]$                 |
| 1     | 0     | 1     | 0   | $\vartheta_4[p_1][p_3]$            |
| 0     | 1     | 1     | 0   | $\vartheta_5[p_2][p_3]$            |
| 1     | 1     | 0     | 0   | $\vartheta_6[p_1][p_2]$            |
| 1     | 1     | 1     | 0   | $\vartheta_7[p_1][p_2][p_3]$       |
| 1     | 0     | 0     | 1   | $\vartheta_8[p_1][P]$              |
| 0     | 1     | 0     | 1   | $\vartheta_9[p_2][P]$              |
| 1     | 1     | 0     | 1   | $\vartheta_{10}[p_1][p_2][P]$      |
| 1     | 1     | 1     | 1   | $\vartheta_{11}[p_1][p_2][p_3][P]$ |

Table 12: Logic for the transcriptional regulation underlying the adjustable gates, *i.e.* regulation of G1, for the two cases considered in the main text (Eq. 12 & Eq. 15 respectively). The Table on the left refers to the case for which G1 behaves as an **AND** gate for low  $p_3$ , and an **OR** gate for high  $p_3$ . The table on the right is for the opposite case.

$$\begin{aligned}
Tr_{G1}^{Adjustgate1} &\propto \frac{z_{on1}}{z_{on1} + z_{off1}}, \\
z_{on1} &= \theta_8[p_1][p_3][P] + \theta_9[p_2][p_3][P] + \theta_{10}[p_1][p_2][P], \\
z_{off1} &= 1 + \theta_1[p_1] + \theta_2[p_2] + \theta_3[p_3] + \theta_4[p_1][p_3] + \theta_5[p_2][p_3] + \theta_6[p_1][p_2] + \theta_7[p_1][p_2][p_3],
\end{aligned} \tag{25}$$

$$\begin{aligned}
Tr_{G1}^{Adjustgate2} &\propto \frac{z_{on2}}{z_{on2} + z_{off2}}, \\
z_{on2} &= \vartheta_8[p_1][P] + \vartheta_9[p_2][P] + \vartheta_{10}[p_1][p_2][P] + \vartheta_{11}[p_1][p_2][p_3][P], \\
z_{off2} &= 1 + \vartheta_1[p_1] + \vartheta_2[p_2] + \vartheta_3[p_3] + \vartheta_4[p_1][p_3] + \vartheta_5[p_2][p_3] + \vartheta_6[p_1][p_2] + \vartheta_7[p_1][p_2][p_3].
\end{aligned}$$

| $p$ | $P$ | Rate           |
|-----|-----|----------------|
| 0   | 0   | 1              |
| 1   | 0   | $\psi_1[T]$    |
| 0   | 1   | $\psi_2[P]$    |
| 0   | 0   | $\psi_3[T][P]$ |

| $[p_4]^4$ | $P$ | Rate               |
|-----------|-----|--------------------|
| 0         | 0   | 1                  |
| 1         | 0   | $\chi_1[p_4]^4$    |
| 0         | 1   | $\chi_2[P]$        |
| 0         | 0   | $\chi_3[p_4]^4[P]$ |

Table 13: Logic for the transcriptional regulation for genes G2 & G3 in Fig. 14.

$$\begin{aligned}
Tr_{G2} &= \frac{\psi_2[P] + \psi_3[T][P]}{1 + \psi_1[T] + \psi_2[P] + \psi_3[T][P]} \\
Tr_{G3} &= \frac{\chi_2[P] + \chi_3[p_4]^4[P]}{1 + \chi_1[p_4]^4 + \chi_2[P] + \chi_3[p_4]^4[P]},
\end{aligned} \tag{26}$$

|                   |                   |                   |       |                |       |       |       |       |                |
|-------------------|-------------------|-------------------|-------|----------------|-------|-------|-------|-------|----------------|
| $r_1$             | $r_2$             | $r_3$             | $r_4$ | $r_5$          | $r_6$ | $r_7$ | $r_8$ | $r_9$ | $r_{10}$       |
| $4 \cdot 10^{-4}$ | $4 \cdot 10^{-4}$ | $4 \cdot 10^{-4}$ | v0.01 | 0.01           | 0.01  | 0.01  | 0.01  | 0.01  | $10^{-4}$      |
| $k_1$             | $k_2$             | $\gamma_p$        | $c_0$ | $\gamma_{p_4}$ | $v_1$ | $v_2$ | $v_3$ | $v_4$ | $\gamma_{p_3}$ |
| 1                 | .056              | 0.04              | 0.1   | 0.001          | 0     | 0.001 | 0     | 0.001 | 0.01           |

Table 14: Parameters values for Eq. 15.